Necessary and Sufficient Conditions for Robust Stability of a Class of Nonlinear Systems[1]

Jorge M. Gonçalves, Munther A. Dahleh
Department of EECS
MIT, Cambridge, MA 02139
jmg@mit.edu, dahleh@lids.mit.edu

Abstract

Input-output stability results for feedback systems are developed. Robust Stability conditions are presented for nonlinear systems with nonlinear uncertainty defined by some function (with argument equal to the norm of the input) that bounds its output norm. A *sufficient small gain theorem* for a class of these systems is presented. Then it is also shown that, for the vector spaces $(\ell_\infty, \|\cdot\|_\infty)$ and $(\ell_2, \|\cdot\|_2)$, the sufficient conditions are also *necessary* with some additional assumptions on the systems. These results capture the conservatism of the *small gain theorem* as it is applied to systems that do not need to have linear gain.

1 Introduction

This paper considers the development of necessary and sufficient conditions for the robust stabilization of certain classes of nonlinear plants. The problem of robust stabilization may be stated as follows. Given a nominal plant model and a family of possible true plants, under what condition does some compensator which stabilizes the nominal plant also stabilize every plant in the given family?

The idea that a loop of less than unity gain ensures stability of a feedback loop has been appreciated since the early days of classical control. In mathematical terms, it is related to well-known ideas on invertibility of nonlinear operators of the form $I + G_1G_2$ where I is the identity and G_1, G_2 are nonlinear operators on Banach spaces.

The usual form of the small gain theorem assumes gain properties of the form

$$\|(Mu)_T\| \leq \gamma\|u_T\| \qquad (1)$$

for the operator M where u denotes the input signal, $\gamma = \sup_{x\neq 0}\frac{\|Mx\|}{\|x\|}$, and u_T denotes the truncation of the signal u at time T. With this structure, it is shown that, if M is linear, for $p = 2, \infty$ if $\|\Delta\|_{\ell_{p-ind}} < 1$ then the feedback system of Δ and M achieves robust stability if and only if $\|M\|_{\ell_{p-ind}} \leq 1$. For details, see [1]. For a nonlinear M, the result is shown only for $p = 2$ (see [6] or [7]).

In [5] a new notion of stability for nonlinear systems is introduced. There, a generalization of (1) is given to allow more general bounding functions of the form

$$\|(Mu)_T\| \leq f(\|u_T\|)$$

where $f(\cdot)$ is a monotone function. Systems satisfying the last inequality are called monotone stable.

While conditions for sufficiency were shown with this new notion of nonlinear gain (also used by others like [8] or [9]) no results on the necessity of such conditions are known. Such results are useful to understand the degree of conservatism that the small gain theorem has. Necessity conditions for linear gain exists (see [1] or [3]). There also exists necessity conditions for nonlinear systems that have their output norm bounded by a linear function of the input norm (see [6] or [7]).

In this paper, an extension of the small gain theorem presented in [5] will be given. Using this theorem we will present sufficient conditions on M in order to guarantee robust stability. For a certain class of perturbations, these conditions on M will be simplified. Then, for the vector space $(\ell_\infty, \|\cdot\|_\infty)$ we will give conditions on M so that the sufficient conditions are also necessary with either NLTV or NLTI perturbations. For the vector field $(\ell_2, \|\cdot\|_2)$ we will also give conditions on M so that the sufficient conditions are necessary with non causal perturbations. The construction of a causal perturbation is still under investigation.

2 Preliminaries

We start by defining some standard concepts. The set of nonnegative integers is denoted by Z_+. The extended space of sequences in $\Re^n$ is denoted by ℓ_{pe} for every $1 \leq p \leq \infty$ or just by ℓ when it is obvious or when it just does not matter what $p-norm$ is being used. The restriction of f to the interval $[a, b]$ is denoted by $f|_{[a,b]}$. For every $f = \{f(0), f(1), \cdots\} \in \ell$ define $\|f\|_{p|_{[a,b]}}$ as $\|f\|_{p|_{[a,b]}} = \left(\sum_{n=a}^{b} |f(n)|^p\right)^{1/p}$.

The set of all $f \in \ell$ with $f \notin \ell_p$ is denoted by $\ell \setminus \ell_p$. Given $f \in \ell$ define $f^x = (f(0)^x, f(1)^x, f(2)^x, ...)$ and the support of $f \in \ell$ by $supp(f) = \{n : f(n) \neq 0\}$.

For $k \in Z_+$, S_k denotes the kth-shift (time-delay) operator on ℓ, and P_k the kth-truncation operator on ℓ. Let $H : \ell \to \ell$ be an operator. Then, H is called causal if $P_kHf = P_kHP_kf$, $\forall_{k\in Z_+}$, strictly causal if $P_kHf = P_kHP_{k-1}f$, $\forall_{k\in Z_+}$, and time invariant if $HS_1 = S_1H$.

Let X_e and Y_e be two signal spaces. Then an operator $G : X_e \to Y_e$ provides an input-output system representation.

The following definition provides a concept of input output stability.

[1] Research supported in part by the Portuguese "Junta Nacional de Investigação Científica e Tecnológica" under the program "PRAXIX XXI", by the NSF under grant ECS-9157306, by the AFOSR under grant AFOSR F49620-95-0219, and by the Draper Laboratory under grant DL-H-441684